

C2N-SPWS300

300 Watt Cresnet Power Supply

Crestron control systems can put a friendly face on any complete integrated AV or automation solution. To support the myriad touchpanels, keypads, and other peripherals that make up a control system, the C2N-SPWS300 provides a convenient and compact centralized power and termination solution.

Intelligent Power Distribution

The C2N-SPWS300 is a 300 Watt regulated power supply designed for powering a large network of Cresnet devices. Power is supplied on eight individually managed outputs. Each output is rated for up to 75 Watts, with a total system rating of 300 Watts. Electronic circuit breaker protection is provided on every output, which can be individually monitored and reset from the control system. The voltage level at each output can even be monitored along with ambient temperature and fault status for the complete power supply system.

Sequential Switching

To minimize current inrush upon startup, the C2N-SPWS300 implements sequential switching of its eight outputs. The startup process may be activated automatically when AC power is applied, or when 24 Volts DC is sensed coming from the control system or another power supply.

Cresnet Distribution

Connected to the Master port of any 2-Series Crestron control system, the C2N-SPWS300 provides a total Cresnet distribution solution. Carrying both data and power, the 16 Cresnet ports afford great flexibility for the termination of numerous Cresnet devices, with easy expansion using **C2N-HBLOCK** termination blocks. It is also ideally designed to enhance the built-in Cresnet distribution capabilities of the **PAC2** Professional Automation Control System.

Versatile Mounting Options

The C2N-SPWS300 can be installed in a Crestron **CAEN** Automation Enclosure using the optional **CAEN-MK** (sold separately), or rack mounted using the optional **C2N-RMAK** (sold separately). Alternately, the C2N-SPWS300 may simply be placed on a shelf or mounted to any vertical surface using its built-in mounting flanges.

- > 300 Watt regulated power supply
- > 8 independently managed outputs
- > 16 Cresnet distribution ports
- > Cresnet monitoring and control
- > Expands the Cresnet power and distribution capabilities of any 2-Series control system

SPECIFICATIONS

Load Ratings

Per Channel: 75 Watts (3.125 Amps) @ 24 Volts DC regulated

System Total: 300 Watts (12.5 Amps) @ 24 Volts DC regulated

Ripple / Noise: <150 mV

Load Protection: Electronic circuit breaker per channel, each rated at 75 watts nominal / 100 watts maximum; 4 Amp, 125V internal fuse; all channels shut off in case of total system overload

Sequential Startup: Outputs activate sequentially when power supply system is enabled (see PWR ON, PWR OFF/SLAVE control)



Power Requirements

4 Amps, 100-240 Volts AC, 50/60 Hz

Connections

- 1 - 8:** (16) 4-pin 5mm detachable terminal blocks comprising (2) paralleled Cresnet ports per each of (8) output channels; 24 Volt DC power outputs with Cresnet data pass-thru from NET port
- NET:** (1) 4-pin 5mm detachable terminal block; Ordinarily connects to the Master Cresnet port of a control system; Cresnet data 'Y' and 'Z' terminals pass through to ports 1 - 8; Applying 24 Volts DC to the '24' and 'G' terminals enables the power supply system when in "SLAVE" mode
- AC Line:** (1) attached input power cable (~1 ft long) with inline IEC320 socket; Connects to grounded AC power source using 3-prong power cable or pigtail cable, both provided

Controls

- PWR ON, PWR OFF/SLAVE:** (1) rocker switch; enables/disables the power supply system if no external DC voltage is applied to the NET port, or selects "SLAVE" mode to allow enabling the power supply system remotely by applying an external 24V DC signal to the NET port
- RESET 1 - 8:** (8) miniature pushbuttons; each resets its respective output channel, or momentarily disables the channel while held
- SYSTEM RESET:** (1) miniature pushbutton; resets all output channels sequentially, or momentarily disables all channels while held
- SETUP:** (1) miniature pushbutton; used for touch-settable ID (TSID)

LED Indicators

- PWR 1 - 8:** (green) Indicate 24V DC power present at each channel output
- OVRLD 1 - 8:** (red) Indicate a load in excess of 75 watts on a given channel, channel output disabled
- SYSTEM OVRLD:** (red) Indicates a total load in excess of 300 watts on the power supply system, all channels disabled
- PWR:** (green) Indicates power supply system is enabled
- NET:** (yellow) Indicates communication with Cresnet system
- SETUP:** (red) Used for touch-settable ID (TSID)

C2N-SPWS300 300 Watt Cresnet Power Supply

Environmental

Temperature: 41° to 104°F (5° to 40°C)

Humidity: 10% to 90% RH (non-condensing)

Enclosure

Chassis: Aluminum, black anodized with polycarbonate label overlay, convection-cooled, vented top and sides

Mounting: Surface mount using (2) integral mounting flanges, or 3U 19-inch rack-mountable (**C2N-RMAK** rack kit sold separately)

CAEN Automation Enclosure: Occupies 1 module space in a single-width enclosure, or 2 side-by-side module spaces in a double-width enclosure (**CAEN-MK** mounting kit sold separately)

Dimensions

Height: 5.19 in (13.18 cm)

Width: 13.25 in (33.66 cm)

Depth: 3.29 in (8.36 cm)

Weight

5.3 lb (2.4 kg)

AVAILABLE ACCESSORIES

C2N-RMAK: Rack Mount Kit

CAEN-MK: CAEN Automation Enclosure Mounting Kit

C2N-NPA8: Cresnet Network Poll Accelerator

C2N-SPWS300 300 Watt Cresnet Power Supply

