



TR2060

Stereo groundloop isolator RCA male - 3.5mm jack

The TR2060 is a basic bidirectional ground loop isolator, designed to electrically isolate audio devices from each other. Hum in audio systems is usually caused by ground loops in the system. A common mode current will flow in a ground loop created by an electrical system that has grounds on different voltage potentials. This results in a 50 Hz hum in the audio signal. The most common method to solve these problems is an audio isolation transformer such as the TR2060 which always need to be in reach for every audio technician. When ground loop problems are encountered, these can be solved in a jiffy, by using the TR2060.



System specifications:

Turn ratio		1 : 1
Frequency	Range (-10 dB)	20 Hz - 20 kHz
THD+N (@ 1 kHz)		< 0.1%
Connectors		3.5 mm Jack male to 2 x RCA female

Product Features:

Dimensions	35 x 35 x 65 mm (W x H x D)
Weight	0.050 kg
Construction	Metal
Colours	Black

Shipping & Ordering:

Packaging	Polybag
Shipping weight & volume	1.030 kg - 0.0054 Cbm (20 pcs)